

Gain and resistance values specified in module file.

keeCI4:  
GK501-4 = .402E-2  
RK501-2 = .624E+4


PARAMETERS:

GK .402E-2  
RK .624E+4



## Knowles CI Analog Standard Response

Module File: keeCI4



GYRATOR MODEL  
Gyrator between node pairs (1,2) and (3,4) having a gyrator constant K


```
.SUBCKT GYR-X 1 2 3 4 PARAMS:K=1
R1 1 2 9E+12
R2 3 4 9E+12
R3 2 3 9E+12
G1 1 2 VALUE = {V(3,4)/K}
G2 3 4 VALUE = {-V(1,2)/K}
.ENDS
```

\*CMAG models a capacitive impedance in series with a  
\*resistor to create a 45 degree phase angle at all  
\*frequencies. The net impedance varies as 1 over the  
\*square root of frequency.

\*CMAG is the capacitor's value at 1 kHz.  
\*Also called VRMAG, VCMAG in older models

```
.SUBCKT CMAG-X 1 2 PARAMS:CMAG = 1
R1 1 2 1E+12
G1 1 2 FREQ {(,707*V(1,2)*(CMAG*6282)) =
+ (20,-17,45)
+ (20000,13,45)
.ENDS
```

Module File: kerCI1



Add 144dB to convert output to dB SPL

Tubing and coupler specified in Knowles Sheet 2.1  
[8mm x 1.0mm ID] + [28mm x 1.5mm ID] + [25mm x 2.0mm ID] + [18mm x 3.0mm ID]

Knowles Electronics LLC  
1151 Maplewood Drive  
Itasca, IL 60143  
(630) 250-5100

Page Size: A

Revision: 9

April 2007

Page 1 of 1